

32262

ET 042903491 US

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Application of

Paul S. Christian and Chad S. Klotzle

for

COMPRESSION JOURNAL

mjdP:\DATA\DIAMOND\32262\REGULAR\PTO\APP.PTO

Background of the Invention

This is a nonprovisional patent application claiming priority of provisional patent application Serial No. 60/181,590 filed February 10, 2000.

Field of the Invention

This invention relates to microwave rotary joints, and in particular to a contacting compression journal for improving performance at the electrical interface of a rotor and a stator.

Description of Related Art

Rotary joints have a long history of applications for the transfer of microwave signals across a rotating interface. To accomplish the transfer of microwave energy across the rotor and stator of a rotary joint, traditional approaches are to use either a contacting or noncontacting interface. In either case, efficient electrical transfer is necessary to minimize signal loss and also to maximize isolation in multiple channel rotary joints.

Noncontacting rotating interfaces employ overlapping longitudinal sections, known as chokes, sized to an axial dimension that is ideal for a particular frequency. Chokes are sized to correspond to the quarter wavelength of a particular frequency and thereby achieve containment of the signal without physical contact at the rotating junction. The advantage of a

noncontacting interface is that all physical wear is eliminated. Disadvantages of this approach are size and weight, particularly at lower frequencies, which have longer wavelengths and therefore require longer chokes.

5

Contacting rotating interfaces traditionally use journals at the electrical junction. Such journals provide a contact of conductive materials at the rotor/stator interface in order to form an electrical short and minimize signal loss. The advantage of a contacting journal is that size can be greatly reduced when compared to a $1/4$ wavelength choke interface. Disadvantages of the contacting journal are increased torque, the need for a tight and perfectly concentric fit of the rotating interface, and the fact that contact stress in rotation causes wear and ultimate electrical failure at the rotating interface.

20

Microwave energy in a rotary joint propagates along a cylindrically shaped conductive path. In order to continue a cylindrical path at the rotating interface the contact fit of a journal is driven radially to form a tight contacting transition, which is necessary for efficient transfer of the energy. Traditional journals consist of overlapping cylinders or sleeves sized such that the outer diameter of the inner sleeve contacts the inner diameter of the outer sleeve along a certain axial distance. Electrical performance of a journal is

reliant on precise alignment of the interface and subsequent retention of the alignment as the rotary joint wears through use. Precise alignment of the journal interface is difficult and has limited the use of contacting rotary joints, despite significant advantages of size and weight.

Summary of the Invention

It is therefore an object of this invention to provide a compression journal for maintaining a continuous electrical contact between a segmented stator ring and a rotor of a rotary joint.

It is another object of this invention to provide a rotary joint journal having increased operational life.

It is yet another object of this invention to provide a rotary joint journal that generates low torque.

It is an object of the present invention to provide lower manufacturing costs for a rotary joint having a compression journal.

It is an object of the invention to provide a compression O-ring around sectional pieces of a cylindrical contact journal to enable easy assembly and a long period of alignment under rotation in a rotary joint.

These and other objects are further accomplished by a compression journal comprising at least two circularly shaped segments, a cylindrical shaft having the circularly shaped segments positioned around the shaft, and means, positioned around the outside of the segments, for maintaining electrical contact between the segments and the cylindrical shaft. The segments comprise a silver impregnated graphite material. The cylindrical shaft comprises a coin silver sleeve around an

5 outer portion of the shaft for contacting the circularly shaped segments. The journal comprises a shield for securing the journal within a stator assembly and blocking RF signal leakage. The means for maintaining electrical contact between the segments and the cylindrical shaft comprises a rubber O-ring. The means for maintaining electrical contact between the segments and the cylindrical shaft comprises a conductive O-ring. The compression journal is positioned within a rotary joint.

The objects are further accomplished by a rotary joint comprising a rotor assembly having a housing and a shaft extending outward from a center portion thereof, a stator assembly having a cylindrical opening for receiving the shaft of the rotor assembly, the housing of the rotor assembly being secured within a housing of the stator assembly, a cavity in the stator assembly for receiving at least two circularly shaped segments positioned around the shaft of the rotor assembly, and means positioned around the outside of the segments for maintaining electrical contact between the segments and the shaft of the rotor assembly. The rotary joint comprises a shield, having an opening for the shaft to pass therethrough, positioned against an end of the circularly shaped segments for securing the segments within the cavity of the stator. The shield provides a ground connection between

5 the circularly shaped segments and the stator housing. The segments comprise a silver impregnated graphite material. The cylindrical shaft comprises a coin silver outer sleeve for contacting the segments. The means for maintaining electrical contact between the segments and the shaft comprises a rubber O-ring. The means for maintaining electrical contact between the segments and the shaft may also comprise a conductive O-ring. The cavity of the stator assembly comprises a channel having a predetermined width within the cavity for receiving the means for maintaining electrical contact between the segments and the shaft. The housing of the rotor assembly comprises a bearing ring positioned around an outer end portion of the housing to facilitate rotation of the rotor assembly when positioned within the stator assembly. The rotor assembly comprises a first capacitive feed ring through which the shaft extends and the stator assembly comprises a second capacitive feed ring through which the shaft passes, the first capacitive feed ring being positioned in close relationship to the second capacitive feed ring when the rotor assembly is positioned within the stator assembly.

20

The objects are further accomplished by a method of providing a compression journal comprising the steps of providing at least two circularly shaped segments, positioning the circularly shaped segments around a cylindrical shaft, and

5 providing means around the outside of the circularly shaped segments for maintaining electrical contact between the segments and the cylindrical shaft. The step of providing at least two circularly shaped segments comprises the step of providing silver impregnated graphite segments. The step of positioning the circularly shaped segments around a cylindrical shaft comprises the step of providing a coin silver sleeve around an outer portion of the shaft for contact with the circular shaped segments. The step of providing means for maintaining electrical contact between the segments and the cylindrical shaft comprises the step of providing a rubber O-ring. Also, the step of providing means for maintaining electrical contact between the segments and the cylindrical shaft comprises the step of providing a conductive O-ring. The method comprises the step of attaching a metal shield over an end of the circularly shaped segments for blocking RF signal leakage.

20 Additional objects, features and advantages of the invention will become apparent to those skilled in the art upon consideration of the following detailed description of the preferred embodiment exemplifying the best mode of carrying out the invention as presently perceived.

Brief Description of the Drawings

5 The appended claims particularly point out and distinctly claim the subject matter of this invention. The various objects, advantages and novel features of this invention will be more fully apparent from a reading of the following detailed description in conjunction with the accompanying drawings in which like reference numerals refer to like parts, and in which:

FIG. 1. is a cross-sectional view of a prior art contacting journal for a rotary joint;

FIG. 2 is a cross-sectional view of the contacting journal of FIG. 1 taken along lines 2-2.

FIG. 3 is a cross-sectional view of the invention showing split rings of a stator surrounding a shaft of a rotor, and two spaced apart O-rings positioned around the split rings;

FIG. 4 is an end view of the compression journal showing a radial shield attached to the stator housing;

FIG. 5 is an exploded perspective view of the rotor assembly of the rotary joint employing the invention;

20 FIG. 6 is an exploded perspective view of the stator assembly of the rotary joint employing the invention;

FIG. 7 is a side view cutaway of the rotary joint showing the rotor assembly inserted within the stator assembly;

FIG. 8 is a side elevational view of the single channel, hollow shaft rotary joint comprising the compression journal;

FIG. 9 is an end view of the rotary joint showing a strip line power divider disposed within the rotary assembly; and

FIG. 10 is a cross-sectional view of a rotary joint having a noncontacting rotation interface comprising a quarter wavelength choke.

5

FIG. 8 is a side elevational view of the single channel, hollow shaft rotary joint comprising the compression journal;

Description of Illustrative Embodiment

Referring to FIG. 1 and FIG. 2, FIG. 1 is a cross-sectional view of a prior art contacting journal 10 for a rotor joint positioned within a metallic housing or stator assembly 12. FIG. 2 is a cross-sectional view of the contacting journal of FIG. 1 along lines 2-2. The contacting journal 10 comprises a cylindrical silver impregnated graphite sleeve or stator 14. A metallic shaft or rotor 16 is inserted within the hollow stator 14 and the outer circumference of the shaft 16 comprises a coin silver sleeve 18 which contacts the silver impregnated graphite sleeve of the stator 14. The contacting journal fits within a cavity of the stator assembly 12 which may comprise aluminum, brass or stainless steel. The contacting journal 10 provides for contact of conductive materials at the rotor 16 and stator 14 interface in order to form an electrical short and minimize signal loss; however, this results in increased torque, a need for a tight and perfectly concentric fit of the rotating interface, and contact stress during rotation which causes wear and ultimate electrical failure at the rotating interface.

Referring now to FIG. 3 and FIG. 4, FIG. 3 is a cross-sectional view of the invention showing a contacting compression journal 19 positioned within a metallic housing or stator housing 26. FIG. 4 is an end view of the compression

journal 19 showing a radial shield 30 covering the end of the compression journal and attached to the stator housing 26. The compression journal 19 is used in microwave and high frequency rotary joints that require a contacting interface.

5 The compression journal 19 comprises two semi-circular spaced ring segments 20a, 20b which are made from silver impregnated graphite. Each ring segment is placed around a coin silver sleeve 44 portion of shaft 46 which extends from a rotor assembly 25 such that there is a small air gap 21 at each ring segment intersection as shown in FIG. 4. The air gap 21 is on the order of 0.003 inches to 0.008 inches. This insures a complete interference fit over the coin silver sleeve 44, and prevents the ring segments 20a, 20b from closing up too much assuring easy, blind assembly. The outer diameter of the ring formed by the two ring segments 20a, 20b is dependent on space available in the rotor assembly 25, but should be thick enough for mechanical integrity of the segments 20a, 20b.

20 When the segments 20a, 20b are placed over the coin silver sleeve 44, O-ring 24 is placed over the outside of the ring segments 20a, 20b to provide a slight compression of the silver impregnated graphite ring segments 20a, 20b onto the coin silver sleeve 44. The O-ring 24 is embodied by diametrical compressive material. More than one O-ring may be placed around the ring segments 20a, 20b, such as O-rings 22, 24 in

the embodiment shown in FIG. 3, depending on the length of the ring segments 20a, 20b for a particular rotary joint design. When the compression journal 19 is positioned within a cavity 45 of the stator housing 26, the cavity 45 comprises one or more channels 54, 56 for receiving each O-ring 22, 24, respectively. The width of each channel 54, 56 along with the characteristics of the O-ring determines the slight compression of ring segments 20a, 20b that is exerted on the coin silver sleeve 44. For example, in the embodiment shown in FIG. 3 the width of the channel is approximately 0.080 inches and the depth of the channel is approximately 0.050 inches. The O-rings 22, 24 are made of rubber and may be embodied by Part No. 2-015 manufactured by Apple Rubber Products, Inc. of Lancaster, New York. Different sizes of O-rings 22, 24 may be used depending on the size of the journal. Different rubber materials may also be used along with different channel depths depending on temperature extremes and desired torque. The O-rings may also be made of conductive material such as an EMI material available from Chomerics, Division of Parker Hannifin of Woburn, Massachusetts.

Referring to FIG. 3, the silver-graphite split ring segments 20a, 20b, being compressed by one or more O-rings 22, 24 onto a diametrically aligned coined silver sleeve 44, can be implemented in the other ways. For example, the beryllium-

5 copper ring can be replaced by conductive O-rings instead of using rubber O-rings. The number of O-rings used depends on the size of the journal and the amount of compression required. Multiple O-rings ensure even compression along the length of the journal as well. The length of the journal may also vary depending on the amount of isolation required.

Referring to FIG. 4, the beryllium-copper radial shield 30 is placed over the end of split ring segments 20a, 20b and secured to the stator housing 26 by screw fasteners 31. The radial shield 30 comprises a plurality of equally spaced-apart radial slots 35 which allow the ring to flex when holding the journal 19 in place. The applied axial compression on the journal 19 assures positive electrical contact with the journal, but can also be adjusted by bending the slotted fingers so that the axial compression does not overcome the radial compression induced by the O-rings 22, 24.

20 The radial shield 30 inhibits RF energy leakage from passing through this area. The radial shield 30 is placed in a non-rotational interface and it is not critical for the dynamic RF seal. Also, as discussed above, conductive O-rings may be used as an RF shield in place of the beryllium shield 30. The choice of which type of shield to use is primarily based on cost and availability of the parts. Material other than beryllium-copper may be used as long as the material exhibits

5 similar properties. The air gap 21 is shown at the ring segment intersections. Also, shown in FIG. 4 is the cylindrical shaft 46 having a coin silver sleeve 44 surrounding the outer portion of the shaft 46 and the O-ring 24 around the circumference of the ring segments 20a, 20b.

The compression journal 19 improves electrical parameters in a rotary joint 50 such as improved isolation between microwave channels of a multi-channel rotary joint, reduced noise within the device, improved electrical contact in the axial direction, whereas a traditional journal bearing may contact anywhere along the axial length during rotation, causing changes in electrical performance, provides a more uniform, concentric and axial contact, reduced insertion loss within the device, and resists rotational effects on electrical performance. Also, because the contact is purely resistive with a very low resistance, the compression journal 19 is frequency insensitive.

20 The compression journal 19 also has mechanical benefits over a traditional journal bearing arrangement such as requiring a much shorter bearing length to provide a better electrical contact; shorter length allows the rotational torque to be lower than a traditional journal; allows a higher non-concentricity on rotor/stator housings while maintaining integrity and performance; longer lasting with virtually no

wear once the joint is properly assembled and run-in; provides a complete circumferential contact; provides more predictable torque with greater consistency between units; and provides greater reliability over temperature.

5 Referring now to FIG. 5, an exploded perspective view of the rotor assembly 25 of the rotary joint 50 is shown. The rotor assembly 25 comprises the rotor housing 28, the shaft 46 having an outer sleeve 44 and extending from the housing 28, a pair of bearings 34a, 34b and a bearing ring 38 which screws onto the threads 30 on the end edge of the rotor housing 28 for securing the bearings 34a, 34b on the outside of the rotor housing 28. A capacitive feed ring 4 comprises two terminals 41a, 41b and has a center hole 47 for the shaft 46 to extend therethrough. The terminals 41a, 41b fit into holes within the housing for connection to a stripline power divider 37 mounted within the rotor housing 28 (FIG. 4). The rotor housing 28 may be made with aluminum, brass or stainless steel.

20 Referring to FIG. 6, an exploded perspective view of the stator assembly 26 of the rotary joint 50 is shown. The two semi-circular ring segments 20a, 20b having an O-ring 24 positioned around the outside surfaces of the ring segments 20a, 20b are inserted within the cavity 45. The cavity 45 comprises a channel for receiving the O-ring 24 and if there is more than one O-ring, then the cavity will have another channel

5 for the additional O-ring. The radial shield 36 is secured to a base wall of the stator housing 26 covering the end of the split rings 20a, 20b by screw fasteners 31. Another capacitive feed ring 42 is provided which comprises two terminals 43a, 43b and has a center hole 49 for the rotor shaft 46 to extend therethrough and into the cavity 45. The terminals 43a, 43b fit into holes within the housing for connection to a stripline power divider mounted within an end portion 21 of the stator housing 26. A ring 51 screws into the screw threads 29 on the inside of the stator housing 26 and secures the rotor assembly 25 within the stator assembly 27. The stator housing 26 may be made with aluminum, brass or stainless steel.

Referring to FIG. 7, a side view cutaway of the rotary joint 50 shows the rotor assembly 25 inserted within the stator assembly 27 and the shaft 46 of rotor assembly 25 inserted within the cavity 45 of the compression journal 19 and extending through the stator assembly 27. The split ring segments 20a, 20b surround the coin silver sleeve 44 of the shaft 46 and the O-ring 22 is position around the ring segments 20a, 20b. The path of RF signal flow is indicated by the arrows 39. The capacitive feed ring 40 of the rotor assembly 25 is disposed adjacent to the capacitive feed ring 42 of the stator assembly 27 when the rotary joint 50 is assembled.

20

5 One of the major advantages of the compression journal is the decreased amount of space required to achieve a good electrical and mechanical contact. This advantage is especially evident at lower microwave frequencies. Rotary joints are primarily used to cover frequencies from 1 to 40 Ghz (although rotary joints are made that go lower and higher). At lower frequencies such as 1 Ghz, the $1/4$ wavelength can be quite long, such as 2.95 inches. FIG. 10 shows a prior art non-contacting $1/4$ wavelength choke. Using the compression journal 19, length was decreased substantially from the prior art journal. Also, the compression journal 19 results in a more balanced design as well as the benefits listed above.

20 Referring to FIG. 8, a side elevational view of the single channel, hollow shaft rotary joint 50 is shown comprising the rotary assembly 25 mounted within the stator assembly 27, and showing connectors 32 and 38 for receiving and sending microwave signals. Rotor shaft 46 is shown extending from the stator assembly 27, which may be used to turn the rotor of another rotary joint. The compression journal 19 of FIG. 7, which is used within the rotary joint 50, enables the outside dimensions of rotary joint 50 to be approximately 3.0 inches high and 1.5 inches wide. However, one skilled in the art will recognize that the physical dimensions of the rotary joint 50 comprising the compression journal 19 will vary depending on

microwave frequencies being used and the specifications for a particular microwave application.

Referring now to FIG. 9, an end view of the rotary joint 50 of FIG. 8 is shown having an outside diameter of 3 inches. The stripline power divider 37 is shown mounted within the rotor assembly 25 which is connected to connector 32. The ends 37a, 37b of the power divider 37 make electrical contact with the terminals 41a, 41b of capacitive feed ring 40 within the rotor assembly 25.

Referring to FIG. 10, a cross-sectional view of a rotary joint 60 is shown having a noncontacting rotational interface comprising a quarter wavelength choke 66. The rotary joint 60 comprises a rotor assembly 62 inserted within a stator assembly 64. The rotor assembly 62 comprises a shaft 65, bearings 68, 70, a capacitive feed ring 72, an RF connector 76 and a coax line 77. The stator assembly 64 comprises an open area for receiving the rotor assembly 62 and a cavity for the shaft 65 to extend through the stator assembly 64. Space between the rotor shaft 65 and an inside wall of the rotor assembly 62 forms the quarter wavelength choke 66. This type of rotary joint 60 has a leakage path 78 because it is impossible for the quarter wavelength choke 66 to provide 100% isolation over any microwave band; it is typically designed for one frequency, and at the midpoint of the desired passband. The prior art contact

journal (FIG. 1) and the compression journal 19 (FIG. 3) are frequency independent.

Referring to FIGS. 1, 2, 3 and 10, the compression journal 19 provides increased life, increased reliability and consistency of operation between various units which result from the split ring segments 20a, 20b being compressed by one or more O-rings 22, 24 (FIG. 3). With the prior art contacting journal of FIGS. 1 and 2, each journal had to fit precisely, requiring rework to get an exact fit. If the rotor and stator are not precisely aligned, a good contact may be difficult to achieve. Once the prior art contacting journal has been worn down just a little, such as 0.0005 to 0.001 inches, the contact is lost. The quarter wavelength design of FIG. 10 has its life limited only by the bearings and the seals. The compression journal 19 of FIG. 3 does not need to be fitted as precisely as the prior art contacting journal to achieve a good contact, but it does require a run-in time period for the split journal to align itself and burnish itself in. If there is some slight axial misalignment, the compression journal 19 will adjust by means of the compression in the O-rings. As the silver-graphite alloy ring begins to wear, the compression from the O-rings 22, 24 will continue to pull the split ring segments 20a, 20b in radially to assure good contact. Reliability and consistency are increased as well due to the decrease in

required precision and the predictable compression of the O-rings.

5 This invention has been disclosed in terms of certain embodiments. It will be apparent that many modifications can be made to the disclosed apparatus without departing from the invention. Therefore, it is the intent of the appended claims to cover all such variations and modifications as come within the true spirit and scope of this invention.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
22